



INVERTER GASOLINE GENSET

Continuous Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a constant electrical load. Average load can be 100%. The generator must not be overloaded.

Standby Power

The maxpower available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utilitypower outage or under test conditions for up to 200 hrs of operation per year under average of 70%load.Overloading isn't permissible.

Prime Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%. The generator can be overloaded 10% for 1 hour per 12 hrs.

Genset

Standby	kVA	2,2
Prime	kVA	2
Start System		Recoil Start
Power Factor	CosΦ	1.0
Voltage		220(50HZ)
Fuel Type		Gasoline
Fuel Tank Capacity	lt	6,5

Engine

Model		148F
Kw (Standby/Prime)		2 / 1,8
Bore / Stroke	mm	48,6 x 43
Number of Cylinder		1
Displacement	cc	80
Oil Capacity	lt	0,35
Engine Type		4-Stroke, Air Cooled,OHV

Size

Weight	kg	19
L x W x H	cm	53 x 34 x 56